

```

1  /*
2  * Scola Tutorial
3  * by Antoine B. Rauzy
4  * Electric-circuit with cloning
5  */
6
7  block ElectricCircuit
8      block PowerSource
9          Boolean outPower true
10     end
11     block Switch1
12         Boolean _closed true
13         Boolean inPower false
14         Boolean outPower false
15         assertion Powering
16             set outPower (if _closed inPower false)
17         end
18     end
19     clones Switch1 as Switch2 end
20     block Lamp
21         Boolean inPower false
22     end
23     assertion Powering
24         set Switch1.inPower PowerSource.outPower
25         set Switch2.inPower Switch1.outPower
26         set Lamp.inPower Switch2.outPower
27     end
28 end
29
30 scenario Light as ElectricCircuit
31     scenario Switch1Lane as Switch1
32         state Initial
33         task Switch
34             set _closed (not _closed)
35         end
36         next Initial Switch
37         next Switch Switch
38     end
39     clones Switch1Lane as Switch2Lane as Switch2 end
40 end
41

```